

Menus for Paint Can RGBW and Channel Assignments.

Display Root Menu	Sub-menu	Sub-menu	Description	Title
STAT	R.(0-255)			Setting a Static output for the light. If there is no dmx input the fixture will default to the static output.
	G.(0-255)			
	B.(0-255)			
	W.(0-255)			
	S.(0-20)		Strobe. 0 is off. 20 = max strobe	
	Z.(0-255)		Zoom from 60° to 10°	
DMX	d.(1-512)		DMX Address set	Different Profiles for the Paint Can. See Profile table for channel definitions.
PRES	12CH		12 channel mode	
	4CH		4 channel mode	
	5CH		5 channel mode	
	6CH		6 channel mode	
	7CH		7 channel mode	
	8CH		8 channel mode	
ID	Id.(01-66)			ID Set
SET	REST	↑↓↑↓	Reset	
	IDSW	ON	ID Function on	
		OFF	ID Function off	
	BSW	ON	White balance on	
		OFF	White balance off	
	CURE	CUR0	Dim Curve linear	
		CUR1	Dim Curve 1	
		CUR2	Dim Curve 2	
		CUR3	Dim Curve 3	
	DIM	OFF	No delay in dimming (0)	
		DIM1	Slight delay in dimming (1)	
		DIM2	Increased delay in dimming (2)	
		DIM3	Further increase in delay (3)	
		DIM4	Maximum delay in dimming (4)	
	POWS	ON	Power protection on	
		OFF	Power protection off	
KEY	ON		Password Protection	
	OFF		↑↓↑↓ Enter	
TEMP	-25°C-100°C		Display of running temp	
PWMF	1.2-24K		refresh rate adjustment	
RUN	DMX/STMT			
CAL 1	RED	0-255		User adjustable so that
	GREEN	0-255		the maximum output at
	BLUE	0-255		255 will reflect the CAL 1
	WHITE	0-255		Values.

Profiles for the Paint Can RGBW.

5Channel

CH	Data	Function	
1	0-255	0-100%, Red	
2	0-255	0-100%, Green	
3	0-255	0-100%, Blue	
4	0-255	0-100% White	
5	0-255	0-100%, Zoom (60°-10°)	

6Channel

CH	Data	Function	
1	0-255	0-100%, Master Dimmer	
2	0-255	0-100%, Red	
3	0-255	0-100%, Green	
4	0-255	0-100%, Blue	
5	0-255	0-100%, White	
6	0-255	0-100%, Zoom (60°-10°)	

12Channel

CH	Data	Function	
1	0-255	0-100%, Master Dimmer	
2	0-255	0-100%, Red	
3	0-255	0-100%, Green	
4	0-255	0-100%, Blue	
5	0-255	0-100%, White	
6	0-255	0-100%, Zoom (60°-10°)	
7	0-255	In built colors and color temps	
8	0-255	0-100%, Strobe	
9	0-255	Automatic program run	
10	0-255	Automatic program speed	
11	0-255	Fade time for the dimming	
12	0-255	ID address	

4Channel

CH	Data	Function	
1	0-255	Hue	
2	0-255	Saturation	
3	0-255	Brightness	
4	0-255	Zoom (60°-10°)	

7Channel

CH	Data	Function	
1	0-255	0-100%, Master Dimmer	
2	0-255	0-100%, Red	
3	0-255	0-100%, Green	
4	0-255	0-100% Blue	
5	0-255	0-100% White	
6	0-255	0-100% Zoom (60°-10°)	
7	0-255	Fade time for the dimming	

8Channel

CH	Data	Function	
1	0-255	0-100%, Master Dimmer	
2	0-255	0-100%, Red	
3	0-255	0-100%, Green	
4	0-255	0-100% Blue	
5	0-255	0-100% White	
6	0-255	0-100%, Zoom (60°-10°)	
7	0-255	Fade time for the dimming	
8	0-255	0-100%, Strobe	